DSA FFT Analysis

Follow the guided steps below on how to set-up a FFT Analysis in EDM to use with Spider hardware.

Create Test



Last update: 2024/05/29 19:59

dsa:fft

| Create a new FFT | Analysis test: FFT | Analysis | | | | | | | | | |
|---|--|--|---|--|----------------------|-------------------|-------------------|--------------------------|--------|-----------------|----|
| lest name: | FFT Analysis | | | | Append the sequ | ience number | 1 | | | | |
| Test description: | | | | | | | | | | | |
| rest description. | | | | | | | | | | | |
| Use the defa Create test by | ault libraries of the by using a template | previous test of the e. | same type. If default libra | aries were not app | lied before the manu | facturing setting | s will be used. | | | | |
| Select Tem | plate Name | Description | | | | | | | | | |
| | | | | | | | | | | | |
| pider system: | SYS_2597504 | • | | | | | | | | | |
| est directory: | | | | | | | | | | | |
| est an eetory i | C:\Users\Drew\D | Documents\EDM\Spi | der_DSA\FFT Analysis | | C | hoose | | | | | |
| Create new rur | C:\Users\Drew\D | Documents\EDM\Spi un | der_DSA\FFT Analysis | | C | choose | | | | | |
| Create new rur | C:\Users\Drew\D | Documents\EDM\Spi un | der_DSA\FFT Analysis | | C | Choose | | | | | |
| Create new rur | C:\Users\Drew\E n folder for each n | Documents\EDM\Spi | der_DSA\FFT Analysis | | | hoose | | < Back | Next > | Car | 10 |
| Create new rur | C:\Users\Drew\E n folder for each n | Documents\EDM\Spi | der_DSA\FFT Analysis | | | ihoose | | < Back | Next > | Car ? | 10 |
| Create new run ew Test Wizard | C:\Users\Drew\D n folder for each n | Documents\EDM\Spi | der_DSA\FFT Analysis | | 3 | ihoose | | < Back | Next > | Car ? | 10 |
| Create new run ew Test Wizard Please check th Note: Go to Mea | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett | Documents\EDM\Spi un be computed in rea ting to select the sign | der_DSA\FFT Analysis I time. nals to be viewed or save | d. | 2 | Choose | | < Back | Next > | Car ? | 10 |
| Create new rur Wizard Please check th Note: Go to Mea Enable a speci | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno | Documents\EDM\Spi un be computed in rea ing to select the sign plogy of multi-resolu | der_DSA\FFT Analysis I time. I als to be viewed or saved tion spectrum | d. | 2 | ihoose | | < Back | Next > | Car ? | 14 |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Mea Enable a speci This functior | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v | Documents\EDM\Spi un be computed in rea ting to select the sign plogy of multi-resolu with variable resoluti | der_DSA\FFT Analysis I time. hals to be viewed or saved tion spectrum on in frequency domain | d. to achieve higher | accuracy in low freq | ihoose | ee the difference | < Back | Next > | Car ? | 1 |
| Create new rur Create new rur lew Test Wizard Please check th Note: Go to Mea Enable a speci This function Time Streams | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis technol n applies the FFT v | Documents\EDM\Spi un be computed in rea ting to select the sign plogy of multi-resolu with variable resolution | der_DSA\FFT Analysis al time. hals to be viewed or saved tion spectrum on in frequency domain | d. to achieve higher | accuracy in low freq | Lhoose | ee the difference | < Back | Next > | Car ? | 1 |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Age Enable a speci This functior This functior This Streams. APS: Auto Poo | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using | Documents\EDM\Spi un be computed in rea ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai | der_DSA\FFT Analysis I time. hals to be viewed or saved tion spectrum on in frequency domain lable | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | < Back | Next > | Car ? | 14 |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Mea Enable a speci This functior This functior This functior APS: Auto Poo FRF: Frequence FRF: Frequence | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct | Documents\EDM\Spi un be computed in rea ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions | der_DSA\FFT Analysis I time. hals to be viewed or saved tion spectrum on in frequency domain lable | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car ? | 10 |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This functior This functior This functior This function FRF: Frequence CPS: Cross Poi | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa | Documents\EDM\Spi un be computed in read ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als | der_DSA\FFT Analysis | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | . Car ? | |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Mea Enable a speci This functior This functior This functior This Streams APS: Auto Poo FRF: Frequenc CPS: Cross Poo FFT: Linear spi | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa sectra signals with | Documents\EDM\Spi un be computed in rea ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple | der_DSA\FFT Analysis I time. hals to be viewed or saver tion spectrum on in frequency domain lable | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car ? | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This function Time Streams APS: Auto Pow FRF: Frequence CPS: Cross Poi FFT: Linear spi SRS: Shock Re | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa sectra signals with esponse Spectra | Documents\EDM\Spi un be computed in rea ting to select the sign slogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple | der_DSA\FFT Analysis I time. hals to be viewed or saved tion spectrum on in frequency domain lable | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car ? | |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Mee Enable a speci This functior This functior This Streams APS: Auto Poo FRF: Frequenc CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Computi | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa weetra signals with esponse Spectra | Documents\EDM\Spi un be computed in rea- ting to select the sign sology of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple | der_DSA\FFT Analysis I time. hals to be viewed or saved tion spectrum on in frequency domain hable x domain. This signal typ relation and Cross-correla | d. to achieve higher e is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | < Back | Next > | ? ? | 10 |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mee Enable a speci This functior This functior This functior This Streams. APS: Auto Poo FRF: Frequenc CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Computi Cepstrum: Cor | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa ectra signals with esponse Spectra te the correlation of mpute the Inverse | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (IF | der_DSA\FFT Analysis al time. hals to be viewed or saver tion spectrum on in frequency domain lable x domain. This signal typ relation and Cross-correla (T) of spectrum signal | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | < Back | Next > | ? ? | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Meze Enable a speci This functior Time Streams. APS: Auto Poo FRF: Frequenc CPS: Cross Poo FFT: Linear spi SRS: Shock Re COR: Compute Cepstrum: Cor Demodulation | C:\Users\Drew\D n folder for each m he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa tectra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N | der_DSA\FFT Analysis al time. hals to be viewed or saver tion spectrum on in frequency domain lable x domain. This signal typ relation and Cross-correli T) of spectrum signal fachinery | d. to achieve higher te is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car ? | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mease Enable a speci This functior Time Streams APS: Auto Poo FRF: Frequence CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Compute Cepstrum: Cor Demodulation TACHO: Tacho | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa ectra signals with esponse Spectra ie the correlation of mpute the Inverse n Spectra: Demodu ometer | Documents\EDM\Spi un be computed in reating to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocom Fourier transform (If ulation Analysis for N | der_DSA\FFT Analysis al time. hals to be viewed or saves tion spectrum on in frequency domain lable x domain. This signal typ relation and Cross-correla T) of spectrum signal lachinery | d. to achieve higher te is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car ? | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Meaz Enable a speci This functior Time Streams - APS: Auto Poo FRF: Frequence CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Computi Cepstrum: Cor Demodulation TACHO: Tacho FLT: Real time | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa ectra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl | Documents\EDM\Spi un be computed in rea- ting to select the sign ology of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan | der_DSA\FFT Analysis al time. hals to be viewed or saves tion spectrum on in frequency domain lable x domain. This signal typ relation and Cross-correla T) of spectrum signal fachinery nels | d. to achieve higher te is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | ? ? | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Meaz Enable a speci This functior Time Streams a APS: Auto Pov FFF: Auto Pov FFF: Frequence CPS: Cross Pov FFT: Linear spi SRS: Shock Re COR: Computi Cepstrum: Cor Demodulatior TACHO: Tacho FLT: Real time Weasure Time Sta | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa eetra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If Jation Analysis for N lied to all input chan | der_DSA\FFT Analysis al time. hals to be viewed or saved tion spectrum on in frequency domain lable x domain. This signal typ relation and Cross-correla T) of spectrum signal fachinery nels | d. to achieve higher e is rarely used ation) | accuracy in low freq | Lhoose | ee the difference | < Back | Next > | Car | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This function Time Streams APS: Auto Poo FRF: Frequence CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Comput Cepstrum: Cor Demodulation TACHO: Tacho: FLT: Real time Measure Time Sta RMS Pe | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectra Using ectra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu ometer et digital filters appl ats: teak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT signals are always avai set the data and the sign of time data (Autocon Fourier transform (IF ulation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher e is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | C ar | |
| Create new rur Create new rur New Test Wizard Please check th Note: Go to Mee This function This function This function This Streams APS: Auto Pou FRF: Frequence CPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Computi Cepstrum: Cor Demodulation TACHO: Tache Cessure Time Sta RMS Pe Select all | C:\Users\Drew\C n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa ectra signals with esponse Spectral signals exit est the correlation of mpute the Inverse n Spectra: Demodu ometer et digital filters appl ats: eak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign ology of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If Jlation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher e is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | ? ? | |
| Create new rur Create new rur Rew Test Wizard Please check th Note: Go to Mee Enable a speci This functior This functior This function This Streams APS: Auto Poo FRF: Frequenc CCPS: Cross Poi FFT: Linear spi SRS: Shock Re COR: Computi Cepstrum: Cor Demodulatior TACHO: Tacho FLT: Real time Measure Time Sta RMS Pe Select all | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra Using cy Response Funct wer Spectral Signa ectra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: teak PRPk | Documents\EDM\Spi un be computed in rea- ting to select the sign sology of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (IF ulation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher e is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This functior Time Streams. APS: Auto Poo FRF: Frequence CPS: Cross Poi FRF: Frequence CPS: Cross Poi FRF: Frequence CPS: Cross Poi FRF: Shock Re COR: Compute CPS: Construction TACHO: Tache FLT: Real time Measure Time Sta RMS Pe Select all | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectra I Signa tectra signals with esponse Spectra ie the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: tak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan i Avg StDev | der_DSA\FFT Analysis | d. to achieve higher | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car | |
| Create new rur Create new rur Lew Test Wizard Please check th Note: Go to Mee Enable a speci This functior This functior This Streams. APS: Auto Poo FRF: Frequenc COR: Cross Poo FFT: Linear spi SRS: Shock Re COR: Computi CCPS: Computi CCPS: Computi CCPS: Computing FFT: Linear spi SRS: Shock Re COR: Computing FFT: Linear spi SRS: Shoc | C:\Users\Drew\C n folder for each m he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa tectra signals with esponse Spectra te the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: teak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign plogy of multi-resolu with variable resoluti gnals are always avai fFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan i Avg StDev | der_DSA\FFT Analysis | d. to achieve higher te is rarely used ation) | accuracy in low freq | uency band. To s | ee the difference | , click on <u>compar</u> | Next > | Car | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This functior Time Streams. APS: Auto Poo FRF: Frequence CPS: Cross Poo FFT: Linear spi SRS: Shock Re COR: Compute CPS: Conspute Cors: Compute State and the spin state RMS Pe Select all | C:\Users\Drew\D n folder for each m he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa tectra signals with esponse Spectra ie the correlation of mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: teak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign ology of multi-resolu with variable resoluti gnals are always avai fFT tions averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher te is rarely used ation) | accuracy in low freq | Lhoose | ee the difference | , click on <u>compar</u> | Next > | Car | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This functior Time Streams. APS: Auto Poo FRF: Auto Poo FRF: Auto Poo FRF: Frequenc CPS: Cross Poo FFT: Linear spi SRS: Shock Re COR: Compute Cepstrum: Cor Demodulation TACHO: Tacho FLT: Real time Veasure Time Sta RMS Pe Select all | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa ectra signals with esponse Spectra ie the correlation o mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: eak PkPk | Documents\EDM\Spi un be computed in reating to select the sign plogy of multi-resolu with variable resoluti gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher | accuracy in low freq | Lhoose | ee the difference | < Back | Next > | Car | |
| Create new rur Create new rur Iew Test Wizard Please check th Note: Go to Mea Enable a speci This functior Time Streams - APS: Auto Poo FF: Streams - APS: Auto Poo FF: Frequence CPS: Cross Poi FF: Frequence CPS: Cross Poi FF: Linear spi SRS: Shock Re COR: Compute CoR: Compute CoR: Compute CoR: Compute TACHO: Tacho FLT: Real time Measure Time Sta RMS Pee Select all | C:\Users\Drew\D n folder for each n he signal types to asured Signals sett ial analysis techno n applies the FFT v and Time Block sig wer Spectra using cy Response Funct wer Spectral Signa eetra signals with esponse Spectra te the correlation o mpute the Inverse n Spectra: Demodu ometer e digital filters appl ats: tak PkPk | Documents\EDM\Spi un be computed in rea- ting to select the sign ology of multi-resolu with variable resoluti gnals are always avai gnals are always avai FFT tions als averaging in comple of time data(Autocon Fourier transform (If ulation Analysis for N lied to all input chan Avg StDev | der_DSA\FFT Analysis | d. to achieve higher te is rarely used ation) | accuracy in low freq | Lhoose | ee the difference | < Back | Next > | Car | |

In EDM, select to create a new test. From the New Test Wizard, select the **FFT Analysis** test type.

Next, give the test a name and description.

Finally, select the signal types that are wanted. You can select more than one signal type. Additionally, there Time History Stats can be selected to be calculated as well. You are **unable** to add more signal types to be computed once the test is created. Press **Finish** to create the test.

Test Configuration

Before testing, the **Analysis Parameters** must be configured to ensure all the data is properly measured.

Frequency Range (Sampling Rate)- determines the resolution and the span of all time and frequency data blocks. Increasing the sample rate increases time resolution (makes dT smaller) and decreases the time span (Block T) captured. Increasing the sample rate also increases the maximum frequency (Fa) in a spectral block and decreases its resolution (increases dF).

Block size/Line- are the number of samples in each time blocks and the number of (un-aliased) spectral lines in each resulting spectrum. Increasing the block size increases the resolution of the frequency transform and allows lower frequencies to be detected, but it also increases the calculation time and slows down response. The ratio between Lines and Block Size is determined by the characteristics of the A/D converter and its anti-aliasing filter. In general, this ratio is about 0.46, meaning that 1024 samples in the waveform will produce about 0.46 * 1024 = 471 lines in the spectrum.

Window- lets the user choose the window to be applied during FFT operation. Windowing functions can help reduce leakage and increase the precision of the frequency measurement. In general, select Uniform for triggered transients, Hanning for general continuous signals and Flat Top when studying tonal data (such as a rotating machine) and needing extreme accuracy of spectral peaks.

Overlap ratio- sets the proportion of the samples in a time block that are overlapped (redundant with samples in a prior block) when calculating the FFT of (un-triggered) continuous signals. Higher overlap ratios result in faster variance reduction per unit time producing smoother data, but they increase the processing requirements. The Overlap Ratio options are no overlap, 25%, 50%, 75%, 87.5%, 95% and As High As Possible. For most applications employing a symmetrically tapered window function (such as Hanning), an overlap of 50% proves optimal.

Average mode- options include Linear, Exponential, and Peak Hold. Linear averaging treats every block equally. The blocks are simply added together (at each frequency), and the result divided by the Average Number. Exponential averaging is a moving or evolving average that favors the most recently measured block. Old data slowly loses its importance (time exponentially), so that the average is dominated by the current instantaneous spectrum.

Average number- Determines the number of blocks measured for Linear and Peak Hold averages.

LPF cutoff frequency- allows the user to specify the cutoff frequency of the low-pass filter.

| FFT analysis settings ——— | | | |
|---------------------------|-------------|------|--------|
| Frequency range (fa) | 12 kHz | • | Format |
| Block size/Line | 1024/450 | • | |
| Window | Hanning | - | |
| Overlap ratio | No overlap | - | |
| Average mode | Exponential | - | |
| Average number | | 8 🌲 | |
| FFT average on/off | Average off | - | |
| LPF cutoff frequency (Hz) | | 0.00 | |

At the bottom of the window, the **Test Summary** can be found. This displays important stats about the analysis such as the Block Time, Sampling Rate, and Frequency Resolution (dF).

| Test summary — | |
|-------------------------------|--------------------|
| Block T = 0.04 s | dT = 3.90625E-05 s |
| Sampling rate (fs) = 25600 Hz | dF = 25 Hz |
| Frequency range (fa)=11520 Hz | |

Input Channels

The input channels will now need to be set up. All sensors will to be properly configured before testing. The Input Channels menu can be found through **Setup** \rightarrow **Input Channels**.



Measurement Quantity

Defines the physical unit that will be measured by the sensor connected to the channel.**Sensitivity** Sets the proportionality factor for the measurement (millivolts per engineering unit) given as a parameter of the sensor.

Input Mode

There are six modes in which the inputs can operate:

DC-Differential- In the DC-Differential mode, neither of the input connections is referenced to the local ground. The input is taken as the potential difference between the two input terminals, and any potential in common with both terminals is canceled out. The Common Mode Voltage (CMV) will be rejected as long as the overall input voltage level does not saturate the input gain stage. Beware that very high CMV will cause clipping and may damage the input circuitry. Signals with a nonzero mean (DC component) can be measured in this mode.

DC-Single End- In single-ended mode, one of the input terminals is grounded and the input is taken as the potential difference of the center terminal with respect to this ground. Use this mode when the input needs to be grounded to reduce EMI noise or static buildup. Do not use this mode when the signal source is ground referenced or ground loop interference may result. This mode also allows signals with a non-zero mean to be measured.

AC-Differential- AC-Differential is a differential input mode that applies a low-frequency high-pass (DCblocking) analog filter to the input. It rejects common mode signals and DC components in the input signal. Use this when DC and low-frequency AC voltage measurements are not required or when a DC bias voltage is present. The analog high-pass filter has a cutoff frequency of -3dB at 0.3 Hz, and -0.1dB at 0.7 Hz for the IEPE input mode.

AC-Single End- AC-Single End grounds one of the input terminals and enables the DC-blocking analog filter. Use this mode for non-ground referenced sources where measuring the DC or low-frequency components are not required. It shares the same high-pass filter as that of AC-Differential.

IEPE (ICP)- All Crystal Instruments products support IEPE (Integral Electronic PiezoElectric) constant current output type input channels. IEPE refers to a class of transducers that are packaged with builtin voltage amplifiers powered by a constant current. These circuits are powered by a 4 mA constant current source at roughly 21 Volts.

Charge- Some sensors provide a high-impedance charge output. Usually, these are high-sensitivity piezoelectric units that lack a built-in voltage mode amplifier (i.e. IEPE), allowing them to be used in high-temperature environments. The Spider-81 front-end module has a built-in charge amplifier that

allows the system to read the output of these sensors.

High-Pass Filter

Ability to set a digital high-pass filter for specific channels.

Integration/Differentiation Channels can be set up to be integrated or differentiated. For example, the velocity data can be integrated from an accelerometer. **NOTE**: if this is selected, the original quantity of data will not be recorded (Ex. If an accelerometer is integrated, there will only be velocity data, no acceleration data.)

From: https://help.go-ci.com/ - **Crystal Instruments Help**

Permanent link: https://help.go-ci.com/dsa:fft?rev=1717012761

Last update: 2024/05/29 19:59