


Setting Up Limit Channels

In some cases, monitor accelerometers placed on the DUT will want to be limited to ensure that the DUT itself does not experience increased dangerous levels. To do this, Limit Channels can be enabled to make sure that these levels are not reached. Here is how to set this up.

1. Go to **Setup** → **Test Configuration** → **Limit Channels**
2. Select the channel that is to be limited and check the **Enabled** box.



3. A limit profile window will open. Specific High Abort and High Alarm limits can be set up.

Limit Profile For Channel: Ch2

Legend: HighAbort(f) (red line), HighAlarm(f) (orange line), profile(f) (green line)

Y-axis: (g)²/Hz (0.0001, 0.001, 0.01)

X-axis: Frequency (Hz) (20, 100, 1000, 2000)

Options: High abort, High alarm, Notching, Low alarm, Low abort, Define all limits together

Frequency (Hz)	Reference ((g)²/Hz)	Enable	High abort (dB)	High alarm (dB)
20	0.0010878	<input checked="" type="checkbox"/>	6	3
2000	0.0010878	<input type="checkbox"/>	6	3

Buttons: Import..., Export CSV, Edit table, Rescale, Insert row, Remove row, Clear table, Fill all, Fill down, Fill range..., Digital output, OK, Cancel

4. A notching limit can also be created. This type of limit will decrease the drive output to make sure that the limit is not met.

Limit Profile For Channel: Ch2

Show dB
 Show profile

Import...
Export CSV
Edit table
Rescale
Insert row
Remove row
Clear table
Fill all
Fill down
Fill range...
Digital output

High abort High alarm Notching Low alarm Low abort Define all limits together

All limits

Frequency (Hz)	Reference ((g)²/Hz)	Enable	High abort (dB)	High alarm (dB)
20	0.0010878	<input type="checkbox"/>	6	3
		<input checked="" type="checkbox"/>		
2000	0.0010878	<input type="checkbox"/>	6	3

OK Cancel

From:
<https://help.go-ci.com/> - **Crystal Instruments Help**

Permanent link:
<https://help.go-ci.com/vcs:limitchannels?rev=1715872279>

Last update: **2024/05/16 15:11**