

How to Create a New Spider System

A test in EDM requires hardware to run. This hardware is represented as a **Spider system**, which consists of one or more Spider modules. This article walks through connecting your Spider modules and creating a new Spider system in EDM.

Prerequisites

- One or more Spider modules, powered on and connected to the PC's network.
- All modules must be on the **same subnet** as the PC. See [How to Connect the Spider System to the PC](#) for IP configuration details.
- The first module must be set as the **“master”** (flip the switch to **“M”**); all other modules are **“slaves.”**

Steps to Create a Spider System

1. Click **Hardware** in the top toolbar, or navigate to **Setup > Select Hardware**.
2. Choose **Select 1 module** or **Select system (1+ modules)**.
3. Click **New system**.
4. In the **Detected modules** section, select each module to add to your system.
5. Set the first module as the master, and all other modules as slaves.
6. Click **OK**.

Managing Spider Systems

To manage existing Spider systems, go to **Tools > Spider Configuration**. If this option is disabled, disconnect from the current Spider system first.

The **Spider System Configuration** window allows you to:

- Create new Spider systems.
- Rename or delete existing systems.
- Set default systems for tests.
- Configure IP addresses.
- Set up digital I/O.
- Synchronize the Spider's datetime clock with the PC.
- Import and export Spider system configurations as SSK files.

Troubleshooting

If the PC does not detect your Spider modules:

- Confirm all modules and the PC share the same subnet (first three numbers of the IP address)

must match).

- Verify connectivity with the **ping** command in the Command Prompt (e.g., ping 172.0.0.100).
- Disable other network adapters, or raise the network priority of the Spider adapter.
- Check that Ethernet cables/ports are functioning and power adapters are supplying adequate power.

For a full walkthrough of IP setup and troubleshooting, see [How to Connect the Spider System to the PC](#).

From:

<https://help.go-ci.com/> - **Crystal Instruments Help**

Permanent link:

<https://help.go-ci.com/general:createnewspidersys?rev=1789669213>

Last update: **2026/09/17 18:20**